

# Powerpack MEMO F9 Series

ONLINE UPS  
6-10kVA  
Single Phase / Single Phase

Computer Room, Network Center,  
Communication System,  
Automation Control System and  
Other Critical Systems



- 1 Intelligent Slot
- 2 Dry Contact
- 3 USB Port
- 4 EPO (Emergency Power Off)
- 5 Parallel Port
- 6 Input Switch
- 7 Terminal Block
- 8 Maintenance Switch



- N +1 Parallel Redundancy
- Online Double Conversion with DSP Control
- Input Current Harmonic: <3%
- Optimization Battery Group, the Quantity of Battery: 16/18/20 Pieces (Optional)
- High Output Power Factor at 0.9 PF
- Wide Input Voltage Range:120-276Vac
- Wide Input Frequency Range (50Hz: 45-55Hz / 60Hz: 54-66Hz )
- Support Generator Input
- Support Economic (ECO) Operation Mode
- Self-Testing When UPS Startup
- Options: SNMP Card / Relay Card / Parallel Card
- Cold Start

6kVA • 10kVA

MODEL		
Capacity	6kVA / 5400W	10kVA / 9000W
<b>INPUT</b>		
Nominal Voltage	220 / 230 / 240VAC	
Operating Voltage Range	120-276Vac	
Operating Frequency Range	50Hz: 45-55Hz; 60Hz:54-66Hz (Auto Sensing)	
Power Factor	≥0.99	
Bypass Voltage Range	Max. Voltage: 220V:+25% (Optional +10%, +15%, +20%)	
	230V: +20% (Optional +10%, +15%)	
	240V: +15% (Optional +10%)	
	Min. Voltage: -45% (Optional -20%, -30%)	
ECO Range	Same as the Bypass	
Harmonic Distortion (THD)	<3% (100% Linear Load)	
Generator Input	Support	
<b>OUTPUT</b>		
Rated Voltage	220 / 230 / 240VAC	
Power Factor	0.9	
Voltage Regulation	±1%	
Frequency	Line Mode	±1%, ±2%, ±4%, ±5%, ±10% of the rated frequency (optional)
	Bat. Mode	50/60 (±0.1) Hz
Crest Factor	3:1	
Harmonic Distortion (THD)	≤2% with linear load	
	≤5% with non-linear load	
Efficiency	>93.5%	
<b>BATTERY</b>		
Battery Voltage	±96/108/120Vdc (Optional)	
Capacity (Standard Unit)	12V/7Ah/9Ah	
Typical Charge Time	6-8 hours (to90% of full capacity)	
Charge Current	1A (Standard unit); Long run unit Max. current 10A (charge current can be set according to battery capacity installed)	
<b>SYSTEM FEATURES</b>		
Transfer Time	Mains to Battery: 0ms; Mains to Bypass:0ms	
Overload	Line Mode	Load≤110%: last 60min, ≤125%: last 10min, ≤150%: last 1min, >150%: turn to bypass mode immediately
	Bypass Mode	40A (Breaker)   60A (Breaker)
Short Circuit	Hold Whole System	
Overheat	Line Mode: Turn to Bypass; Backup Mode: Shut down UPS immediately	
Low Battery Voltage	Alarm and Switch off	
Self-Diagnostics	Upon Power On and Software Control	
Battery	Advanced Battery Management	
Audible & Visual Alarms	Line Failure, Battery Low, Overload, System Fault	
LED & LCD Display	Line Mode, Bat. Mode, ECO Mode, Bypass Mode, Battery Low, Overload & UPS Fault	
LCD Display	Input Voltage, Input Frequency, Output Voltage, Output Frequency, Load Percentage, Battery Voltage, Inner Temperature & Remaining Battery Backup Time	
Communication Interface	RS232, USB, SNMP card (Optional), Parallel card (Optional), Relay card (Optional)	
<b>ENVIRONMENT</b>		
Operating Temperature	0°C ~40°C	
Storage Temperature	-25°C ~55°C	
Humidity Range	0-95% (non-condensing)	
Altitude	< 1500m	
Noise Level	≤55dB (1m)	
<b>PHYSICAL</b>		
Dimension (WxDxH) (mm)	250 x 502 x 616	
Net Weight (kg)	62 / 18	64 / 20
<b>STANDARDS</b>		
Safety	IEC / EN62040-1, IEC / EN60950-1	
EMC	IEC / EN62040-2, IEC61000-4-2, IEC61000-4-3, IEC61000-4-4, IEC61000-4-5, IEC61000-4-6, IEC61000-4-8,	
<b>BATTERY BANK</b>		
Model	MEMO F9-BT Series	
Battery Type & Max. Quantity	2 x 20pcs / 7Ah / (9Ah)	
<b>PHYSICAL OF BATTERY BANK</b>		
Dimension (WxDxH) (mm)	597 x 250 x 616	
Net Weight (kg)	122 / 134	

Makelsan reserves the right to change or modify product design, construction, specifications, or materials without prior notice and without incurring any obligation to make such changes and modifications on Makelsan products previously or subsequently sold. Makelsan does not guarantee the items of the accuracy and completeness.