

## BH201 1500V Fuse Holder



### FEATURES:

ADLER BH201 touch safe fuse holders are designed for all standard 14x51mm PV fuses such as ADLER A74 series. With current ratings up to 30A at 1500 VDC, this holder provides the most compact and effective solution to protect 1500 VDC circuits and equipment in photovoltaic applications.

**Note:** SCCR is limited to the interrupting rating of the installed fuse or 10kA, which ever is less.

### DESCRIPTION:

The BH201 touch safe holder is designed for 14x51mm fuse links and is equipped with a red indicator light. It will light up when the circuit is interrupted.

### SPECIFICATIONS:

- Rated Voltage: 1500 VDC
- Rated Current: up to 30 A
- Short Circuit Current Rating(SCCR): DC 10kA
- Standards: UL 4248-18, EN 60947-3  
(10 kA@1500 VDC)
- Max. Dissipation: 8 W
- Material Flammability: UL 94-V0
- Mounting: DIN Rail mounting
- Wire Range: 5-13 AWG
- Operation Temperature: -40°C to +150°C
- UL Listed File: E486822
- TUV File: R 50393975

### DIMENSIONS: mm

