



## HA5

---

The HA5 converts HDMI to SDI or HD-SDI. Up to eight channels of HDMI audio are embedded into the SD/HD-SDI output allowing a convenient single cable audio/video connection. The HA5 provides two SD/HD-SDI outputs and supports long HDMI cables on the input. The HA5 is useful for connecting HDMI cameras to SD/HD-SDI equipment.

<https://www.aja.com/products/ha5>

---

### Video Formats

---

- (HD) 1080p 23.98, 24, 25, 29.97, 30
- (HD) 1080i 50, 59.94, 60
- (HD) 720p 50, 59.94, 60
- (SD) 625i, 525i

### Input

---

- HDMI with embedded audio

### Outputs

---

- SMPTE-259/292/296 SDI/HD-SDI, 2 x BNC

### Size (w x d x h)

---

- 4.6" x 2.4" x 1" (117mm x 61mm x 25mm)

### Power

---

- +5VDC Regulated, 4 watts, power supply required (included with purchase)

### Environment

---

- Safe Operating Temperature: 0 to 40 degrees C (32 to 104 degrees F)
- Safe Storage Temperature (Power OFF): -40 to 60 degrees C (-40 to 140 degrees F)
- Operating Relative Humidity: 10-90% noncondensing
- Operating Altitude: <3,000 meters (<10,000 feet)